















Wearable BT UHF Reader.

This is a newly-developed wearable UHF reader that enables read distance of 9m. By adapting wrist strap or arm strap, it can be attached to mobile phone, tablet and other devices by magnetic attachment. It features removable battery, performs data transmission via Type C USB, and enables user information interaction via Bluetooth coordinated with APP or SDK.

And it also can be paired with Android/IOS device to expand RFID capability. This RFID reader can be suitable for warehousing, power inspection, asset management, retail, etc., which provides users with more flexibility to efficiently finish their tasks at hand.



Specifications

Physical Characteristics	
Dimensions	108 mm × 78 mm × 18 mm
Weight	200 g / 7.05 oz.
Port	Type C USB
Button	ON/OFF, SCAN
Battery	2000 mAh (removable)
Charging Current	5 V / 1.5 A
Charging Duration	2 hours
Identification Lamp Button	Red lamp (Red lamp lights up constantly when charging)
	Green lamp (Green lamp lights up constantly when charged)
	Blue lamp (Blue lamp lights up constantly when battery amount is higher than 20%, Blue lamp flashes when battery capacity is lower than 20%.)
	BT connection identification lamp (BT doesn't pair when blue lamp is OFF, BT has paired when blue lamp is ON.)
Developing Environment	
Operating System	Android/IOS SDK Supported
Security	RFID Encrypted Module (Reserve)
Communication	
Type C USB	USB connection to realize data transfer
ВТ	Bluetooth 4.0

User Environment		
Operating Temp.	-20 °C to +60 °C	
Storage Temp.	-40 °C to +70 °C	
Humidity	5%RH - 95%RH non condensing	
Dropping	1.2m dropping on concrete	
Sealing	IP65	
UHF		
Engine	Based on Impinj Indy R2000	
Antenna parameter	Circular Polarized Antenna (3dBic)	
Frequency	920-925 MHz / 902-928 MHz / 865-868 MHz	
Protocol	EPC C1 GEN2 / ISO18000-6C	
Power	1W (30dBm, support +5~+30dBm adjustable)	
	2W Optional (33dBm, for Latin America, etc.)	
R/W range	> 9 m (open outdoors, Impinj MR6 tag)	
Reading rate	> 200 tags/s	

^{*}Ranges and rates depend on tags and environment

Accessories (Optional)

Wrist strap, arm strap, magnetic handle